



139.95 EUR

incl. 19% VAT, plus [shipping](#)

- Intel WiFi, Intel WiDi !
- Dual Gigabit LAN !
- Gigabyte Features !
- NVMe M.2 slot !



- Supports 7th/ 6th Generation Intel® Core™ Processors
- Dual Channel Non-ECC Unbuffered DDR4, 2 DIMMs
- Intel® USB 3.1 Gen 1 with USB Type-C™
- Intel® Optane™ Memory Ready
- Ultra-Fast M.2 with PCIe Gen3 x4 & SATA interface
- ALC1220 120dB SNR HD Audio with Smart Headphone Amp
- 802.11ac Dual Band 867Mbps wireless supports MU-MIMO and BT4.2
- Dual Intel® GbE LAN with cFosSpeed Internet Accelerator Software
- Smart Fan 5 features Multiple Temperature Sensors and Hybrid Fan Headers
- Ultra Durable™ Metal Shielding over PCIe Slots
- GIGABYTE UEFI DualBIOS™
- APP Center Including Cloud Station™ Utility

CPU	<ol style="list-style-type: none">1. Support for 7th and 6th generation Intel® Core™ i7 processors/Intel® Core™ i5 processors/Intel® Core™ i3 processors/Intel® Pentium® processors/Intel® Celeron® processors in the LGA1151 package2. L3 cache varies with CPU <p>(Please refer "CPU Support List" for more information.)</p>
Chipset	<ol style="list-style-type: none">1. Intel® H270 Express Chipset
Memory	<ol style="list-style-type: none">1. 2 x DDR4 DIMM sockets supporting up to 32 GB of system memory * Due to a Windows 32-bit operating system limitation, when more than 4 GB of physical memory is installed, the actual memory size displayed will be less than the size of the physical memory installed.2. Dual channel memory architecture3. Support for DDR4 2400* / 2133 MHz memory modules4. Support for ECC Un-buffered DIMM 1Rx8/2Rx8 memory modules (operate in non-ECC mode)5. Support for non-ECC Un-buffered DIMM 1Rx8/2Rx8/1Rx16 memory modules6. Support for Extreme Memory Profile (XMP) memory modules * To support 2400 MHz or XMP memory, you must install a 7th generation processor. <p>(Please refer "Memory Support List" for more information.)</p>
Onboard Graphics	<p>Integrated Graphics Processor:</p> <ol style="list-style-type: none">1. 1 x DVI-D port, supporting a maximum resolution of 1920x1200@60Hz2. 2 x HDMI ports, supporting a maximum resolution of 4096x2160@24Hz or 2560x1600@60Hz * Support for HDMI 1.4 version.3. Support for up to 3 displays at the same time * To set up a triple-display configuration, you must connect a D-Sub monitor using a DVI-to-D-Sub adapter.4. Maximum shared memory of 1 GB
Audio	<ol style="list-style-type: none">1. Realtek® ALC1220 codec2. High Definition Audio3. 2/4/5.1/7.1-channel4. Support for S/PDIF Out
LAN	<ol style="list-style-type: none">1. 2 x Intel® GbE LAN chips (10/100/1000 Mbit)

Wireless Communication module	<ol style="list-style-type: none">1. Wi-Fi 802.11 a/b/g/n/ac, supporting 2.4/5 GHz Dual-Band2. BLUETOOTH 4.2, 4.1, BLE, 4.0, 3.0, 2.1+EDR3. Support for 11ac wireless standard and up to 867 Mbps data rate * Actual data rate may vary depending on environment and equipment.
Expansion Slots	<ol style="list-style-type: none">1. 1 x PCI Express x16 slot, running at x16 (The PCIEX16 slot conforms to PCI Express 3.0 standard.)2. 1 x M.2 Socket 1 connector for the wireless communication module (M2_WIFI)
Storage Interface	<p>Chipset:</p> <ol style="list-style-type: none">1. 1 x M.2 connector on the back of the motherboard (Socket 3, M key, type 2260/2280 SATA and PCIe x4/x2 SSD support)2. 6 x SATA 6Gb/s connectors3. Support for RAID 0, RAID 1, RAID 5, and RAID 10
USB	<p>Chipset:</p> <ol style="list-style-type: none">1. 2 x USB 2.0/1.1 ports available through the internal USB header2. 6 x USB 3.1 Gen 1 ports (4 ports on the back panel, 2 ports available through the internal USB header)3. 1 x USB Type-C™ port on the back panel, with USB 3.1 Gen 1 support
Internal I/O Connectors	<ol style="list-style-type: none">1. 1 x 24-pin ATX main power connector2. 1 x 4-pin ATX 12V power connector3. 6 x SATA 6Gb/s connectors4. 1 x M.2 Socket 3 connector on the back of the motherboard5. 1 x CPU fan header6. 1 x system fan header7. 1 x front panel header8. 1 x front panel audio header9. 1 x USB 3.1 Gen 1 header10. 1 x USB 2.0/1.1 header11. 1 x S/PDIF Out header12. 1 x Clear CMOS jumper13. 1 x chassis intrusion header

	<ol style="list-style-type: none">1. 1 x PS/2 keyboard/mouse port2. 2 x HDMI ports3. 2 x SMA antenna connectors (2T2R)4. 1 x DVI-D port
Back Panel Connectors	<ol style="list-style-type: none">5. 4 x USB 3.1 Gen 1 ports6. 1 x USB Type-C™ port, with USB 3.1 Gen 1 support7. 2 x RJ-45 ports8. 1 x optical S/PDIF Out connector9. 5 x audio jacks (Center/Subwoofer Speaker Out, Rear Speaker Out, Line In, Line Out, Mic In)
I/O Controller	<ol style="list-style-type: none">1. iTE® I/O Controller Chip
H/W Monitoring	<ol style="list-style-type: none">1. System voltage detection2. CPU/System temperature detection3. CPU/System fan speed detection4. CPU/System fan speed control <p>* Whether the fan speed control function is supported will depend on the cooler you install.</p>
BIOS	<ol style="list-style-type: none">1. 2 x 128Mbit flash2. Use of licensed AMI UEFI BIOS3. Support for DualBIOS™4. PnP 1.0a, DMI 2.7, WfM 2.0, SM BIOS 2.7, ACPI 5.0
Unique Features	<ol style="list-style-type: none">1. Support for APP Center * Available applications in APP Center may vary by motherboard model. Supported functions of each application may also vary depending on motherboard specifications. 3D OSD @BIOS Ambient LED AutoGreen BIOS Setup Color Temperature Cloud Station EasyTune Easy RAID Fast Boot Game Boost ON/OFF Charge Platform Power Management Smart Backup Smart Keyboard Smart TimeLock System Information Viewer USB Blocker V-Tuner2. Support for Q-Flash3. Support for Smart Switch4. Support for Xpress Install

Bundle Software	<ol style="list-style-type: none">1. Norton® Internet Security (OEM version)2. Intel® Wireless Display3. Intel® Optane™ Memory Ready4. cFosSpeed
Operating System	<ol style="list-style-type: none">1. Windows® 10 64-bit (for 7th Generation Intel® Processors)2. Windows® 10 64-bit / Windows® 8.1 64-bit / Windows® 7 32-bit / 64-bits (for 6th Generation Intel® Processors) * Please download the "Windows USB Installation Tool" from GIGABYTE's website and install it before installing Windows 7.
Form Factor	<ol style="list-style-type: none">1. Mini-ITX Form Factor; 17.0cm x 17.0cm
Remark	<ol style="list-style-type: none">1. Due to different Linux support condition provided by chipset vendors, please download Linux driver from chipset vendors' website or 3rd party website.2. Most hardware/software vendors may no longer offer drivers to support Win9X/ME/2000/XP. If drivers are available from the vendors, we will update them on the GIGABYTE website.